Product datasheet

Specifications



(!) Discontinued

Main

Range	TeSys
Product Name	TeSys GK1
Product Or Component Type	Fuse-disconnector
Device Short Name	GK1 F
Poles Description	3P

EAN Code: 3389110787733

GK1FK

TeSys fuse-disconnector - 3P - 125A - fuse size 22 x 58 mm

Complementary

Mounting Support	Rail
Mounting Position	Vertical (tolerance: +/- 23°)
Control Type	Toggle
[Ue] Rated Operational Voltage	Power circuit: 690 V AC Signalling circuit: 500 V AC Signalling circuit: 220 V DC
[le] Rated Operational Current	6 A for signalling circuit 125 A for power circuit
Contacts Type And Composition	1 C/O early-break
Fuse Size	22 x 58 mm
Fuse Туре	GG AM
Connections - Terminals	Power circuit: connector 1 cable(s) 1670 mm ² solid Power circuit: connector 1 cable(s) 1650 mm ² flexible without cable end Power circuit: connector 1 cable(s) 1625 mm ² flexible with cable end
Tightening Torque	2 N.m power circuit: on connector

Environment

Standards	IEC 60947-3
Protective Treatment	TC
Ambient Air Temperature For Operation	-5070 °C
Height	128 mm
Width	121 mm
Depth	97 mm
Net Weight	0.86 kg

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1

Contractual warranty

Warranty

18 months

Sustainability

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

Well-being performance

Reach Free Of Svhc	
Toxic Heavy Metal Free	
Mercury Free	
Rohs Exemption Information	Yes
Eu Rohs Directive	Compliant
	EU RoHS Declaration
China Rohs Regulation	China RoHS declaration
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins