# **Product datasheet**

Specifications



() Discontinued

### TeSys D contactor - 4P(4 NO) -AC-1 - <= 440 V 125 A - 32 V DC coil

LP1D80004CW

EAN Code: 3389110227925

#### Main

Range	TeSys	
Range Of Product	TeSys Deca	
Product Or Component Type	Contactor	
Device Short Name	LP1D	
Contactor Application	Resistive load	
Utilisation Category	AC-1 AC-3 AC-3e AC-4	
Poles Description	4P	
[Ue] Rated Operational Voltage	ated Operational Voltage Power circuit: <= 1000 V AC 25400 Hz   Power circuit: <= 300 V DC	
[Ie] Rated Operational Current	125 A (at <60 °C) at <= 440 V AC AC-1 for power circuit	
Jc] Control Circuit Voltage 36 V DC		

### Complementary

complementary	
Compatibility Code	LP1D
Pole Contact Composition	4 NO
Contact Compatibility	M4
Protective Cover	Without
[Ith] Conventional Free Air Thermal Current	125 A (at 60 °C) for power circuit
Irms Rated Making Capacity	1100 A at 440 V for power circuit conforming to IEC 60947
Rated Breaking Capacity	1100 A at 440 V for power circuit conforming to IEC 60947
[Icw] Rated Short-Time Withstand Current	135 A 40 °C - 10 min for power circuit 320 A 40 °C - 1 min for power circuit 640 A 40 °C - 10 s for power circuit 990 A 40 °C - 1 s for power circuit
Associated Fuse Rating	200 A gG at <= 690 V coordination type 1 for power circuit 160 A gG at <= 690 V coordination type 2 for power circuit
Average Impedance	0.8 mOhm - Ith 125 A 50 Hz for power circuit
Power Dissipation Per Pole	12.5 W AC-1
[Ui] Rated Insulation Voltage	Power circuit: 600 V CSA certified Power circuit: 600 V UL certified Power circuit: 1000 V conforming to IEC 60947-4-1
Overvoltage Category	III

Pollution Degree	3
[Uimp] Rated Impulse Withstand Voltage	8 kV conforming to IEC 60947
Safety Reliability Level	B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO 13849-1
Mechanical Durability	4 Mcycles
Electrical Durability	0.8 Mcycles 125 A AC-1 at Ue <= 440 V
Control Circuit Type	DC wide range
Coil Technology	Without built-in suppressor module
Control Circuit Voltage Limits	0.10.3 Uc (-4070 °C):drop-out DC 0.751.2 Uc (-4055 °C):operational DC 11.2 Uc (5570 °C):operational DC
Inrush Power In W	22 W (at 20 °C)
Hold-In Power Consumption In W	22 W at 20 °C
Operating Time	620 ms opening 2035 ms closing
Time Constant	75 ms
Maximum Operating Rate	3600 cyc/h 60 °C
Connections - Terminals	Control circuit: screw clamp terminals 1 14 mm <sup>2</sup> - cable stiffness: flexible without cable end Control circuit: screw clamp terminals 2 14 mm <sup>2</sup> - cable stiffness: flexible without cable end Control circuit: screw clamp terminals 2 12.5 mm <sup>2</sup> - cable stiffness: flexible with cable end Control circuit: screw clamp terminals 1 14 mm <sup>2</sup> - cable stiffness: solid Control circuit: screw clamp terminals 2 14 mm <sup>2</sup> - cable stiffness: solid Control circuit: screw clamp terminals 2 14 mm <sup>2</sup> - cable stiffness: solid Power circuit: connector 1 450 mm <sup>2</sup> - cable stiffness: flexible without cable end Power circuit: connector 2 425 mm <sup>2</sup> - cable stiffness: flexible without cable end Power circuit: connector 1 450 mm <sup>2</sup> - cable stiffness: flexible with cable end Power circuit: connector 2 416 mm <sup>2</sup> - cable stiffness: solid Power circuit: connector 2 425 mm <sup>2</sup> - cable stiffness: solid Power circuit: connector 2 425 mm <sup>2</sup> - cable stiffness: solid Power circuit: connector 2 425 mm <sup>2</sup> - cable stiffness: solid Power circuit: connector 2 425 mm <sup>2</sup> - cable stiffness: solid Power circuit: connector 2 425 mm <sup>2</sup> - cable stiffness: solid Power circuit: connector 2 425 mm <sup>2</sup> - cable stiffness: solid Power circuit: connector 2 425 mm <sup>2</sup> - cable stiffness: solid
Tightening Torque	Control circuit: 1.2 N.m - on screw clamp terminals - with screwdriver flat $\emptyset$ 6 mm Control circuit: 1.2 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 12 N.m - on connector - with screwdriver flat $\emptyset$ 6 to $\emptyset$ 8 mm Power circuit: 12 N.m - on connector hexagonal screw head 4 mm

Standards	CSA C22.2 No 14	
	EN 60947-4-1	
	EN 60947-5-1	
	IEC 60947-4-1	
	IEC 60947-5-1	
	UL 508	
Product Certifications	BV	
	CCC	
	CSA	
	DNV	
	EAC	
	GL	
	LROS (Lloyds register of shipping)	
	UL	

Ip Degree Of Protection

IP20 front face conforming to IEC 60529

Permissible Ambient Air Temperature Around The Device	-6080 °C storage -4060 °C operation 6070 °C with derating	
Operating Altitude	03000 m	
Fire Resistance	850 °C conforming to IEC 60695-2-1	
Flame Retardance	V1 conforming to UL 94	
Mechanical Robustness	Vibrations contactor open (2 Gn, 5300 Hz) Vibrations contactor closed (3 Gn, 5300 Hz) Shocks contactor open (8 Gn for 11 ms) Shocks contactor closed (10 Gn for 11 ms)	
Height	127 mm	
Width	96 mm	
Depth	181 mm	
Net Weight	2.685 kg	

## **Packing Units**

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	20.5 cm
Package 1 Width	11 cm
Package 1 Length	14 cm
Package 1 Weight	2.74 kg

## **Contractual warranty**

Warranty

18 months

#### **Sustainability**

**Green Premium<sup>TM</sup> label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

#### Well-being performance

	Reach Free Of Svhc	
	Toxic Heavy Metal Free	
	Mercury Free	
	Rohs Exemption Information	Yes
	Pvc Free	
Eu R	ohs Directive	Compliant
		EU RoHS Declaration
Chin	a Rohs Regulation	China RoHS declaration
		Pro-active China RoHS declaration (out of China RoHS legal scope)
Wee	e	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins